





FORCE HT SERIES

THREE PHASE HYBRID INVERTERS Also available in AC coupled.

The Energizer® Force HT Series inverter range offers advanced features and is compatible with high-voltage batteries. With the hybrid inverter range, you're able to expand your solar system by adding extra batteries.

There are 5 inverter size options and it can connect to our Powerstack with up to seven battery modules connected in series, allowing for a maximum storage capacity of up to 28kWh.





High Performance Three-Phase Inverters

- Dual-MPPT design with precise MPPT algorithm
- From 97.2% maximum efficiency
- IP65 rated
- Optional export control
- Compact & lightweight
- RS485, Wi-Fi, LAN, GPRS (optional) communications
- Wide voltage range/low start-up voltage
- Android and iPhone apps available
- 10 years warranty







OLAR INVERTERS						
MODEL INPUT	Force 5.0HT	Force 6.0HT	Force 8.0HT	Force 10.0HT	Force 12.0H	
	Force 5.0AT	Force 6.0AT	Force 8.0AT	Force 10.0AT	Force 12.0A	
PV INPUT [ONLY FOR HYBRID]						
Max. Input Power [W]	7500	9000	10400	13000	15000	
Max. Input Voltage [V]			1000			
Start-up Input Voltage [V]			160			
Rated Input Voltage [V]			720			
MPPT Operating Voltage Range [V]			160-950			
Max. Input Current [A]	14/14	14/14	26/14	26/14	26/14	
Max. Short-circuit Current [A]	16/16	16/16	32/16	32/16	32/16	
No. of Independent MPP Trackers	***	444	2	0.11	0/4	
No. of Strings Per MPP Tracker	1/1	1/1	2/1	2/1	2/1	
BATTERY CONNECTION						
Battery Type		Lithium Battery (LFP)				
Battery Voltage [V]		180-600				
Max. Charge/Discharge Current [A]		26.0				
Communication Interface		CAN (Communicate	with Inverter), RS4	85 (Upgrade BMS)		
AC INPUT AND OUTPUT [GRID]						
Max. AC Input Power [VA]	10000	12000	16000	16000	16000	
Max. AC Input Current (per phase)[A]	15.2	18.2	24.2	24.2	24.2	
Rated Output Power [W]	5000	6000	8000	10000	12000	
Max. Output Apparent Power [VA]	5500	6600	8800	11000	13200	
Rated Output Current (per phase)[A]	7.2	8.7	11.6	14.5	17.4	
Лах. Output Current [A]	8.8	10.6	14.1	17.6	21.2	
Rated Grid Voltage [V]		3L/N/PE	380/220; 400/230;	415/240		
Rated Grid Frequency [Hz]			50/60			
Power Factor		1 (adjustable from 0.8 leading to 0.8 lagging)				
THDi		•	<3% @rated power			
PS OUTPUT						
Max. Output Apparent Power [VA]	5000	6000	8000	10000	12000	
Peak Output Apparent Power [60s][VA]	10000	12000	14000	15000	15000	
Max. Current (per phase)[A]	7.2	8.7	11.6	14.5	17.4	
Rated Output Voltage [V]			3L/N/PE 400/230			
Rated Output Frequency [Hz]			50/60			
Power Factor	1 (adjustable from 0.8 leading to 0.8 lagging)					
FHDi (linear load)		<3% @rated power				
SwitchTime [ms]			<20			
EFFICIENCY			-20			
Euro Efficiency	97.8	200/		98.00%		
Max. Efficiency	97.2			97.23%		
Max. Battery Charge Efficiency (PV to BAT)(@full load)	91.2	20 /0	98.50%	97.2370		
Max. Battery Discharge Efficiency (PV to BAT)(@full load)			97.00%			
			91.00%			
PROTECTION			VE0			
nsulation Monitoring			YES			
Residual Current Monitoring		YES				
OC Reverse Polarity Protection		YES				
Anti-islanding Protection		YES				
C Short-circuit Protection		YES				
AC Overcurrent/Overvoltage Protection		YES				
OC Switch		YES				
SFD		DC: Type II / AC: Type III				
AFCI		Option	al (Available in Q3,	2022)		
STANDARD						
Safety		EN 62109-1	EN 62109-2, EN 6	2477-1		
EMC		IEC 61000-6-2, IEC 61000-6-3				
Certification	EN	EN50549-1, C10/11, VDE-AR-N 4105, G98, G99, CEI 0-2 1				
PROTECTION						
Dimensions (WxHxD)[mm]			449*519*198			
Veight [kg]			28			
nstallation			Wall Mounted			
opology			Transformerless			
Cooling Method	Nat	ural		FAN Cooling		
loise Emission [dB]	3	5		45		
Max. Operating Altitude [m]		2000				
Operating Temperature Range [°C]		-25 to 60				
lumidity [No Condensation]			0% to 100%			
Protection Degree			IP65			
Standby Consumption [W]			<15			
Nonitoring Module		Wi-Fi, LAN, 4G, GPRS (optional)				
Communication		2*RS485, DRM, Ripple Control, USB				
Display			LCD, App, Website	, ·		
- F			_ ,pp, oboito			

^{© 2022} Energizer. Energizer and certain graphic designs are trademarks of Energizer Brands, LLC and related subsidiaries and are used under license by 8 Star Energy Pty Ltd. All other brand names are trademarks of their respective owners. Neither 8 Star Energy Pty Ltd nor Energizer Brands is affiliated with the respective owners of their trademarks.